



Perform 7500 T

PORTABLE POWER

50Hz Perform Range

Product advantages

- ➔ Entire group guaranteed 3 years
- ➔ KOHLER Professional Engine
- ➔ Compact frame with protection panels against shocks
- ➔ Good value for money
- ➔ Comfort of prehension thanks to the ergonomic handles

Zoom

QUAD CLEAN AIR FILTER

The Cyclonic Quad Clean_z air filters provide 4 levels of filtration which effectively filter out large particles and capture the finest particles. They ensure a continuous supply of clean air to the engine, fuel economies, increase the engine performance and extend its lifetime

Miscellaneous

The best report performance / price, intended for the frequent manners.



This product is QUALIGEN certified. Defined by the SIMOTHERM and GIGREL professional organisations, the QUALIGEN charter is intended to provide a label for equipment compliant with current regulations (user safety, noise level, power, sales information, After Sales Service) in order to provide the highest level of quality of our and thus to guarantee the users safety.

Perform 7500 T

General specifications

Range	Perform
Frequency (Hz)	50
Max. power (kW)	6.50
Max power. (kVA)	8.15
Nominal voltage (V)	400
Number of phase	Three phase
Acoustic pressure level Lw(A)	97
Noise level dB(A) - 1m	83
Noise level dB(A) - 7m	69

Engine specifications

Engine trademark	Kohler
Engine type	CH 440
Distribution	O.H.V.
Start	Launcher
Fuel	Petrol (unlead)
Autonomy (h)	2.8
Consumption (L/h]	2.6
Tank (L)	7.3
Oil Guard	Yes
Capacity (cm3)	429
Oil capacity (L)	1.1

Alternator specifications

Type	Without collar or brush
Regulation	Mechanical
Protection class	IP 23
Insulation class	H

Plugs and panel descriptive

1 x 2P+T 230V 10/16A - circuit breaker + 1 x 2P+T 400V 32A - circuit breaker

Dimensions and weight

Length (cm)	81
Width (cm)	55.5
Height (cm)	59
Dry Weight (kgs)	96.5

Packaging

Packaging type	Box
Length (cm)	82
Width (cm)	56.5
Height (cm)	60
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	193

Preliminary data

Options

	<p>R03 Differential protection R03 This set includes a differential switch and a thermal circuit breaker.</p>
	<p>R05M Manual changeover switch The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.</p>
	<p>RKS2 Maintenance kit Maintenance kit contain a bottle of oil, a spark plug and an air filter</p>
	<p>RKB1 Trolley kit RKB1 Trolley kit for the generating sets of 6kW or below</p>
	<p>RH1 Cover Loose cover for storing and protecting during the winter</p>
	<p>RPQ Earth spike RPQ For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.</p>
	<p>RBAC Storage box Removable arrangement box</p>
	<p>RPM Set of male plugs RPM Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V</p>

Preliminary data