



ALIZE 6000 E UK

PORTABLE POWER

Generating Sets Range PRESTIGE

PRODUCT ADVANTAGES

- Large Autonomy
- Electric starter with batteries without maintenance
- HONDA Professional Engine
- Very Silent
- Easy movement thanks to the standard wheels

With its extremely low noise level, electric starting and a full socket panel, this genset offers exceptional EASE OF USE.

Range PRESTIGE

Top of the range equipment that is efficient and with low noise emissions, for a wide range of standard requirements.



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

ALIZE 6000 E UK

GENERAL SPECIFICATIONS

Range	PRESTIGE
Frequency (Hz)	50
Max power LTP (kW) *	5.60
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	24
75% cons. (l/h) *	2.50
75% Autonomy (h) *	9.60
Sound power level guaranteed LwA dB(A)	93
Acoustic pressure level @1m in dB(A)	78
Acoustic pressure level @7m in dB(A)	64

ENGINE SPECIFICATIONS

Engine model	HONDA
Engine type	GX390E
Distribution	O.H.V.
Start	Electrical
Oil Guard	Oui
Capacity (cm3)	389
Oil capacity (L)	1.10

ALTERNATOR SPECIFICATIONS

Technology	Without collar or brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 115V 16A socket - circuit breaker + 1 115V 32A socket - circuit breaker + 1 230V 16A socket - circuit breaker + 1 230V 32A socket - circuit breaker + hour meter + indicator

DIMENSIONS AND WEIGHT

Length (cm)	78
Width (cm)	59
Height (cm)	75
Dry Weight (kgs)	130

PACKAGING

Packaging type	Box / Pallet
Length (cm)	80
Width (cm)	61
Height (cm)	89.50
Weight (kg)	147.50
Pallet type	
Number of box by pallet	0
Pallet height (cm)	0
weight of the packaged Pallet (kg)	0



ACCESSORIES SUPPLIED



User and maintenance manual

OPTIONS



R05A **Automatic mains failure panel** Automatic start, remote control, start on dry contact.



R50 **Male plugs 230V/16A** 16A blue 230V male plug - Sold per 1 or 10



R51 **Male plugs 115V/16A** 16A yellow 115V male plug - Sold per 1 or 10



R52 **Male plugs 230V/32A** 32A blue 230V male plug - Sold per 1 or 5



R53 **Male plugs 115V/32A** 32A yellow 115V male plug - Sold per 1 or 5



R54 **Adaptator kit** Adaptator R54 16A/13A adaptator unit. Sold per 1 or 3



R55 **Adaptator kit** ADAPTATOR R55 16A/13A adaptator economy. Sold per 1 or 3



R56 **Adaptator kit** ADAPTATOR R56 16A/13A double adaptator. Sold per 1 or 3



RBH1 **Cans of oil** Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)



RBH0-5 **Cans of oil** Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40).



RPQ

Earth spike

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.



4/28/2015

ALIZE 6000 E UK - PORTABLE POWER - Generating Sets PRESTIGE

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 12bis, rue de la Villeneuve - CS 92848 - 29228 BREST CEDEX 2 - France - Tel +33(0)2 98 41 41 41 - Fax +33 (0)2 98 41 63 07 - www.sdmo.com