



HX 3000 UK

PORTABLE POWER

Generating Sets Range INTENS

PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- HONDA Professional Engine
- Solid and high-performance equipment

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

HX 3000 UK

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50
Max power LTP (kW) *	3
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	3.10
75% cons. (l/h) *	1.30
75% Autonomy (h) *	2.40
Sound power level guaranteed LwA dB(A)	95
Acoustic pressure level @1m in dB(A)	81
Acoustic pressure level @7m in dB(A)	67

ENGINE SPECIFICATIONS

Engine model	HONDA
Engine type	GX200
Distribution	O.H.V.
Start	Starter
Oil Guard	Oui
Capacity (cm3)	196
Oil capacity (L)	0.60

ALTERNATOR SPECIFICATIONS

Technology	Without collar or brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 115V 16A sockets - circuit breaker + 1 socket 230V 16A - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kgs)	41

PACKAGING

Packaging type	Box
Length (cm)	60.50
Width (cm)	46
Height (cm)	44
Weight (kg)	43
Pallet type	140/110
Number of box by pallet	15
Pallet height (cm)	145
weight of the packaged Pallet (kg)	661



ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

OPTIONS



R06

Trolley kit

Trolley kit for 2 and 3 kW generating sets.



R18

Maintenance kit for HONDA engines

Maintenance kit for Honda GX160 and GX200 engine (except Alizé 3000 et SH3000)



R50

Male plugs 230V/16A

16A blue 230V male plug - Sold per 1 or 10



R51

Male plugs 115V/16A

16A yellow 115V male plug - Sold per 1 or 10



R54

Adaptator kit

Adaptator R54 16A/13A adaptator unit. Sold per 1 or 3



R55

Adaptator kit

ADAPTATOR R55 16A/13A adaptator economy. Sold per 1 or 3



R56

Adaptator kit

ADAPTATOR R56 16A/13A double adaptator. Sold per 1 or 3



RBH1

Cans of oil


Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)



RBH0-5

Cans of oil

Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40).



RHO

Protection cover

Cover for SDMO 's generating sets, welding sets and water pumps



RPQ

Earth spike

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.



4/13/2015

HX 3000 UK - PORTABLE POWER - Generating Sets INTENS

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 12bis, rue de la Villeneuve - CS 92848 - 29228 BREST CEDEX 2 - France - Tel +33(0)2 98 41 41 41 - Fax +33 (0)2 98 41 63 07 - www.sdmo.com